

7. MICROPHONE INSTALLATION

Simply Plug the i266 into your headphone Jack socket of the iPad, iPhone and iPod Touch, to operate as shown in the example pictures below.



i266 with recording software on iPad



i266 with LUCI software on iPhone

8. WARRANTY POLICY

MicW Audio warrants that its Products will be free from defects in material and workmanship for one (1) year from the date of purchase by the Original Purchaser.

9. CE MARKING



The MicW i266 microphone conform with the relevant CE mark directives approved by the European commission.

10. SPECIFICATIONS

MICROPHONE i266	
Type	Electret Condenser
Capsule diameter	12mm
Principle of operation	Pressure Gradient
Polar Pattern	Cardioid
Sensitivity (-1 dB)	-40 dB (300mV/10Pa, 1kHz)
Frequency Response	20Hz ~ 20 kHz
S/N ratio	More than 55dB
Impedance	Less than 2.2k
Power Source	Plug-power capability, Plug and play
Operating Temperature	05°C ~ +50°C
Length	55mm
Weight	16g
Connector	3.5mm 4-Pole headset interface

MicW. User's Manual



Cardioid Recording Microphone

www.mic-w.com

1. INTRODUCTION

Welcome to the MicW i series of professional microphones. We have been producing high quality microphones for test and measurement and studio recording for over 20 years. Our unique knowledge of diaphragm technology has enabled us to offer you very high quality products for audio applications.

The i series is designed specifically for the iPad, iPhone and iPod Touch, offering outstanding audio performance for recording and broadcasting.

The i266 is a cardioid microphone with high sensitivity. It is recommended for high quality sound

MicW.

a member of BOWA Technology Ltd.

Unit 1003, North Ring Center, No.18 Yulin Road, Xicheng District
Beijing 100028, China
Phone: +86-10-51281118
Fax: +86-10-62251626
Email: sales@mic-w.com
Web: www.mic-w.com



MicW microphones

Product features and specifications are subject to change without notice.

11. PACKING LIST

- i266 Standard
- i266 microphone
- Windscreen
- User manual

12. Accessories

There are a number of accessories available from MicW. The accessories can be purchased separately.

- Windscreen
- Clip
- 2m Extension cable
- Split cable
- Aluminum tube
- Windjammer

More information can be found at www.mic-w.com

recording, specially for broadcasting, live radio interviews and other live applications.

4. APPLICATIONS

The i266 can be used as a high quality alternative to the internal microphone on the iPad, iPhone and iPod Touch. Use for recording vocals, instruments, musical performances, interviews and meetings where you want to capture high quality sound. The i266 is supplied with a windscreen to reduce wind noise in outdoor environments.

2. SAFETY INSTRUCTION

The microphone is supplied with a pre-polarized capsule which is tested in a high temperature and high humidity environment for more than 24 hours.


3. POWER SUPPLY

The i266 does not require an additional battery for power.



5. DIRECTIONAL CHARACTERISTIC


The i266 is a cardioid microphone. The typical polar pattern is given in the following chart.



Polar Pattern

6. FREQUENCY RESPONSE

The typical frequency response is given in the following chart.



Typical Frequency Response of i266 at 10cm from the source